

# NCTS-QSTROM PRO QPR1000VA (1000VA/800W) Automatic Voltage Regulator

## Model: QPR100800M

### Product Features

- Autonomous voltage control to a given set point
- CPU controlled
- Meter LED Display (Input/Output)
- Status Indicator LEDs
- Precise protection of over voltage and below voltage
- Precise delay time, able to choose long delay time or short delay time
- Input range switch available
- Large AC range of Input Voltage
- USB port
- Simple and fast installation



# NCTS-QSTROM PRO QPR1000VA (1000VA/800W) Automatic Voltage Regulator

## Technical Specifications

### Model: QPR100800M

#### Line Mode Specifications

Rated power (Input 190V)	800W
Actual range of input volotage	100~260V (5 relays)
Frenquency	50Hz/60Hz
Output voltage	220V / 110V±10%
Rated output current	3.5A
Transformer	EI square aluminum transformer
Colour	Black + Silver
Delay time	3S/180S
Protection	High voltage/ Low voltage protection
Operating temperature	0~40°C
Relative humidity	10%RH~90%RH
Dimensions (mm)	640*315*210mm
Weight (kg)	20
Outer package (pcs/box)	4

Attention: only 60% power when input is 160V, 80% power when input is 190V

213 | Zhanwang Digital Plaza | Tianhe District Guangzhou | China

Hongnan High tech Huizhou Huicheng High end Electronic  
Information Innovation Park | Huicheng District | Huizhou City | China  
[www.ncts.cn](http://www.ncts.cn) | email: [info@ncts.cn](mailto:info@ncts.cn)

FZS1BL01 | Jebel Ali Freezone | Dubai | UAE | P.O. Box 17000  
[www.ncts.co](http://www.ncts.co) | e-mail: [info@ncts.co](mailto:info@ncts.co)